

# byd:sign

Model d:5032

50" Precision HDTV

Plasma TV and Receiver



byd:sign Confidential  
Features and specifications are subject to change

## Precision

- Designed with state-of-the-art Pixelworks DNX Technology™\* for motion compensation
- HDTV 1080i supported\* and a 16:9 aspect ratio for a superior, widescreen entertainment experience
- 170 degree viewing angle for a clear picture from nearly every viewing area
- 600:1 contrast ratio and 700 nit brightness for a realistic picture

## Simplicity

- Clean and simple on-screen controls
- Integrated NTSC 181-channel PLL tuner with auto tuning
- Carefully-crafted remote control designed for greater ease-of-use
- Virtually every audio and video connection available

## Innovation

- A custom stand is included and is removable for wall mounting
- Detachable speakers with amplifier complete the entertainment experience

## Specifications

|                                     |   |
|-------------------------------------|---|
| <b>Model</b>                        | d:5032  |
| <b>Part Number</b>                  | 5032-US-001   |
| <b>UPC</b>                          | 872152000166  |
| <b>Container Quantities 40'/20'</b> | 50/25 (Palletized)  |
| <b>Country of Origin</b>            | China   |
| <b>Carton Dimensions (inches)</b>   | 62.2 x 15 x 36.6 (with stand)   |
| <b>Unit Dimensions (inches)</b>     | 56.3 x 11.3 x 32.6 (with stand)   |
| <b>Gross Weight (lb)</b>            | 150   |
| <b>Unit Weight (lb)</b>             | 119.5 with stand and speakers<br>108 w/o stand  |
| <b>Panel Type</b>                   | 50" PDP HD Plasma   |
| <b>Pixel Resolution</b>             | WXGA (1366 x 768)   |
| <b>Video System</b>                 | NTSC  |
| <b>Brightness</b>                   | 700 cd/m2   |
| <b>Audio System</b>                 | Two 10 watt speakers  |
| <b>Tuner Type</b>                   | 181 channel Electronic PLL tuner  |
| <b>TV Features</b>                  | MTS + SAP stereo broadcast<br><br>HDTV 1080i support (requires HD set-top box)<br>Closed caption, Caption-Vision, V-chip<br>Three language on-screen display<br>Off sleep timer |
| <b>Contrast Ratio</b>               | 600:1   |
| <b>Aspect Ratio</b>                 | 16:9  |
| <b>Color Temperature</b>            | 10K   |
| <b>TV Input</b>                     | TV/CATV threaded COAX connector   |
| <b>DVI Input</b>                    | DVI x 1   |
| <b>PC Input</b>                     | Analog D-sub 15-pin   |
| <b>HD Component Input</b>           | Y/Pr/Pb x 2   |
| <b>S-Video Input</b>                | 4-pin DIN x 1   |
| <b>Composite Video Input</b>        | RCA x 2   |
| <b>Video Output</b>                 | RCA x 1   |
| <b>Audio Output</b>                 | RCA L/R x 2; stereo headphone mini-jack   |
| <b>Power Consumption AC</b>         | 480 watts   |
| <b>Table Stand</b>                  | Included  |
| <b>Wall-mount</b>                   | VESA standard wall mountable  |
| <b>Remote Control</b>               | Full-function remote  |
| <b>Limited Warranty</b>             | 1 year parts and labor  |



**pixelworks**

Copyright 2003 byd:sign, inc.  
byd:sign, inc.  
3707 FM 1960 West, Suite 500  
Houston, TX 77068  
(877) 278-1887  
[www.flatisbetter.com](http://www.flatisbetter.com)

\*Pixelworks DNX Technology™ is a trademark of Pixelworks, Inc.